

Simple function, 50 to 600W DC-DC converters

Features

- ◆ High Density
- ◆ Wide Range Input
- ◆ Output adjustment Capability
- ◆ Remote On/Off
- ◆ Fixed Switching Frequency
- ◆ International Safety Approvals
- ◆ Low component count



Key Market Segments & Applications



Specifications								
Model		3.3V	5V	12V	15V	24V	28V	48V
Input range	VDC	24V nom: 18-36, 48V nom: 36-76V, 110V nom: 82-185V, 280V nom: 200-400V						
Output Voltage Adj. Range	VDC	2.97~3.63	4.5~5.5	10.8~13.2	13.5~16.5	21.6~26.4	25.2~30.8	43.2~52.8
Line Regulation	-	0.4% or 20mV (whichever is greater) over entire input range with constant load						
Load Regulation	-	0.8% or 40mV (whichever is greater) from no load to full load with constant input line						
Ripple and Noise	pk-pk	100mV		150mV		240mV	280mV	480mV
Series Operation	-	Possible - Refer to installation manual						
Over Voltage Protection	%	150 - 180%	125 - 145%					
Overload Protection	%	Approximately 105 - 140%, automatic recovery						
Remote On/Off	-	Low = ON, Open = OFF						
Remote Sensing	-	PH100S, PH150S, PH300S, PH600S models						
Parallel operation	-	PH300S & PH600S only: Requires external circuitry						
Inverter Good signal	-	PH300S & PH600S only: Signal available for status of inverter						
Thermal Protection	-	Internal sensing, self resetting						
Cooling	-	Conduction or forced air. See application notes for cooling and heatsink selection						
Operating Temperature Range	°C	Baseplate temperature -20°C to +85°C (100°C on PH300 & PH600). -40°C start up possible - consult factory						
Storage Temperature	°C	-40°C to +85°C (+100°C on PH300 & PH600)						
Temperature Coefficient	-	0.02%/°C						
Isolation	-	Input to output: 3000VAC, Input to Baseplate: 2500VAC(1)						
Isolation Resistance	-	Output to Baseplate -100MΩ at 500VDC and 70%RH						
Safety Agency Certification (1)	-	UL60950-1, CSA60950-1, EN60950-1 and CE Mark.						
Warranty	yrs	Two years						

Note: See Installation Manual for full details, test methods of parameters and application notes

(1) No safety certification on PH50S48-3.3, PH75S48-3.3, PH150S48-3.3

Not Recommended For New Designs

Model Selector						
Nominal Output Voltage (V)	Output Current (A)	Output Power (W)	24V input	48V input	110V input	280V input
3.3	10.0	33.0	-	PH50S48-3.3	-	PH50S280-3.3
3.3	15.0	49.5	-	PH75S48-3.3	-	PH75S280-3.3
3.3	20.0	66.0	-	PH100S48-3.3	-	PH100S280-3.3
3.3	30.0	99.0	-	PH150S48-3.3	-	PH150S280-3.3
3.3	50.0	165.0	-	-	-	PH300S280-3.3
3.3	100.0	330.0	-	-	-	PH600S280-3.3
5.0	10.0	50.0	PH50S24-5	PH50S48-5	PH50S110-5	PH50S280-5
5.0	15.0	75.0	-	PH75S48-5	PH75S110-5	PH75S280-5
5.0	20.0	100.0	-	PH100S48-5	-	PH100S280-5
5.0	30.0	150.0	-	PH150S48-5	PH150S110-5	PH150S280-5
5.0	50.0	250.0	-	-	-	PH300S280-5
5.0	100.0	500.0	-	-	-	PH600S280-5
12.0	4.2	50.0	PH50S24-12	PH50S48-12	PH50S110-12	PH50S280-12
12.0	6.3	75.0	-	PH75S48-12	PH75S110-12	PH75S280-12
12.0	8.4	100.0	-	PH100S48-12	-	PH100S280-12
12.0	12.5	150.0	-	PH150S48-12	PH150S110-12	PH150S280-12
12.0	25.0	300.0	-	-	-	PH300S280-12
12.0	50.0	600.0	-	-	-	PH600S280-12
15.0	3.4	50.0	PH50S24-15	PH50S48-15	PH50S110-15	PH50S280-15
15.0	5.0	75.0	-	PH75S48-15	PH75S110-15	PH75S280-15
15.0	6.7	100.0	-	PH100S48-15	-	PH100S280-15
15.0	10.0	150.0	-	PH150S48-15	PH150S110-15	PH150S280-15
15.0	20.0	300.0	-	-	-	PH300S280-15
15.0	40.0	600.0	-	-	-	PH600S280-15
24.0	2.1	50.0	PH50S24-24	PH50S48-24	PH50S110-24	PH50S280-24
24.0	3.2	75.0	-	PH75S48-24	PH75S110-24	PH75S280-24
24.0	4.2	100.0	-	PH100S48-24	-	PH100S280-24
24.0	6.3	150.0	-	PH150S48-24	PH150S110-24	PH150S280-24
24.0	12.5	300.0	-	-	-	PH300S280-24
24.0	25.0	600.0	-	-	-	PH600S280-24
28.0	1.8	50.0	PH50S24-28	PH50S48-28	PH50S110-28	PH50S280-28
28.0	2.7	75.0	-	PH75S48-28	PH75S110-28	PH75S280-28
28.0	3.6	100.0	-	PH100S48-28	-	PH100S280-28
28.0	5.4	150.0	-	PH150S48-28	PH150S110-28	PH150S280-28
28.0	10.8	302.0	-	-	-	PH300S280-28
28.0	21.5	602.0	-	-	-	PH600S280-28
48.0	6.3	302.0	-	-	-	PH300S280-48
48.0	12.5	600.0	-	-	-	PH600S280-48

Pinout	
Pin Description	Function
-Vin	Negative Input Terminal
+Vin	Positive Input Terminal
+S	Positive Remote sense
-S	Negative Remote sense
+V	Positive Output Terminal
-V	Negative Output Terminal
IOG	Inverter Good Signal
TRIM	Output adjustment trim pin
CNT	On/Off Control Terminal
CS	Current Monitor Signal

Other DC-DC Products	
PH Full Function	50 - 300W, full function versions of PH
PAQ, PAH, PAF	50 - 700W quarter, half & full bricks
PX	10-40W, 12-48V input, DC-DC
CC-E	1.5-30W, 5-48V input, DC-DC

For Additional Information, please visit us.tdk-lambda.com/lp/products/ph-series-sf.htm



Not Recommended For New Designs

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[TDK-Lambda:](#)

[PH100S280-12](#) [PH100S280-15](#) [PH100S280-24](#) [PH100S280-28](#) [PH100S280-3.3](#) [PH100S280-5](#) [PH100S48-12](#)
[PH100S48-15](#) [PH100S48-24](#) [PH100S48-28](#) [PH100S48-3.3](#) [PH100S48-5](#) [PH150S110-12](#) [PH150S110-15](#)
[PH150S110-24](#) [PH150S110-28](#) [PH150S110-5](#) [PH150S280-12](#) [PH150S280-15](#) [PH150S280-28](#) [PH150S280-3.3](#)
[PH150S280-5](#) [PH150S48-15](#) [PH150S48-28](#) [PH150S48-3.3](#) [PH300S280-12](#) [PH300S280-15](#) [PH300S280-28](#)
[PH300S280-3.3](#) [PH300S280-48](#) [PH50S110-15](#) [PH50S110-5](#) [PH50S24-12](#) [PH50S24-24](#) [PH50S24-28](#) [PH50S24-5](#)
[PH50S280-24](#) [PH50S280-3.3](#) [PH50S48-12](#) [PH50S48-15](#) [PH50S48-24](#) [PH50S48-28](#) [PH50S48-3.3](#) [PH50S48-5](#)
[PH600S280-12](#) [PH600S280-15](#) [PH600S280-24](#) [PH600S280-28](#) [PH600S280-3.3](#) [PH600S280-48](#) [PH600S280-5](#)
[PH75S110-15](#) [PH75S110-28](#) [PH75S110-5](#) [PH75S280-12](#) [PH75S280-15](#) [PH75S280-28](#) [PH75S280-3.3](#) [PH75S280-](#)
[5](#) [PH75S48-15](#) [PH75S48-24](#) [PH75S48-28](#) [PH75S48-3.3](#) [PH75S48-5](#) [PH150S48-12](#) [PH50S24-15](#) [PH75S110-12](#)
[PH50S280-15](#) [PH300S280-5](#) [PH150S280-24](#) [PH50S280-5](#) [PH75S48-12](#) [PH75S110-24](#) [PH75S280-24](#) [PH50S110-](#)
[24](#) [PH50S280-12](#) [PH50S110-12](#) [PH150S48-24](#) [PH50S110-28](#) [PH150S48-5](#) [PH300S280-24](#) [PH50S280-28](#)