

1 S 2130 [NEC]		Z-Di	=1S2128[NEC]: 10.8...13.2V	34	DO-1	
1 S 2130(A)[Texas]	Tix	Z-Di	=1S2030[Texas]: 13V	31a	DO-7	+1S2030
1 S 2131 [NEC]	Fui,Nec	Z-Di	=1S2128[NEC]: 17...20V	34	DO-1	+1S2128
1 S 2132 [NEC]		Z-Di	=1S2128[NEC]: 80...115V	34	DO-1	
1 S 2133 [NEC]		Z-Di	=1S2128[NEC]: 115...140V	34	DO-1	
1 S 2134	Fui,Hit,Nec	Si-Di	SS, 30/40V, 45/135mA, Uf<1V(40mA), <7ns	31a	DO-35	BA 318, BAY 38, 1N4305, 1N4148...49, ++
1 S 2135	Fui,Hit,Nec	Si-Di	SS, 60/70V, 0.25/0.75A, Uf<1V(0.1A), <7ns	31a	DO-35	BAW 62, BAX 95, 1N4446...49, 1N4148...49++
1 S 2136	Hit	Z-Di	5.4...6.6V, 0.25W	2	TO-1	BZX55/..., BZX79/..., ZPD..., 1N5232...43,++
1 S 2137		Z-Di	=1S2136: 7.5...10V	2	TO-1	
1 S 2138		Z-Di	=1S2136: 10.8...13.2V	2	TO-1	
1 S 2139(A...C)	Njr	C-Di	VHF AFC/Tuning	31a	DO-41	BB 105, BB 205, BB 305, BB 405, BB 505++
1 S 2140	Fui	Si-Di	SS, 60V, 0.25A, <6ns	31a	=DO-35	BAW 62, BAX 95, 1N4446...49, 1N4148...49++
1 S 2142	Sak	C-Di	Dual, FM/VHF,Tuning/AFC	12j	(9x6x4mm)	BB 104, BB 204, BB 304, MV 104, ++
1 S 2143	Sak	C-Di	Dual, FM/VHF,Tuning/AFC	12j	(9x6x4mm)	BB 104, BB 204, BB 304, MV 104, ++
1 S 2144(A...C)	Sak	Si-Di	SS, 40V, 0.15A, 5ns	31a	DO-41	BA 200...201, BAW 46, BAX 80, 1N4148...49+
1 S 2145	Sak	Si-Di	SS, 90V, 0.1A, <5ns	31a	DO-35	BA 219, 1N4446...49, 1N4148...49
1 S 2147(A...D)	Sak	C-Di	VHF AFC/Tuning	31a	DO-35	BA 105, BA 205, BA 305, BA 405, BA 505++
1 S 2148	Sak	Si-Di	Rr, Dual, 100V, 1.5A, Uf<0.95V(0.75A)	12j	(14x12x5)	2x(BY226...227, BY251...255, 1N5392...99++)
1 S 2149		Si-Di	=1S2148: 200V	12j	(14x12x5)	2x(BY226...227, BY251...255, 1N5393...99++)
1 S 2148R...2149R		Si-Di	=1S2148:	12h	(14x12x5)	2x(BY226...227, BY251...255, 1N5393...99++)
1 S 2150(A)[Texas]	Tix	Z-Di	=1S2030[Texas]: 15V	31a	DO-7	+1S2030
1 S 2160(A)[Texas]	Tix	Z-Di	=1S2030[Texas]: 16V	31a	DO-7	-1S2030
1 S 2175	Nec	GaAs-Di	SS, 7.5V, 0.05A	Koax	SOD-31	
1 S 2176	Org	Si-Di	kV-Rr, 6kV, 0.1A, <500ns	=31a	(19x9x7mm)	BYX 90, 1N5183
1 S 2177	Org	Si-Di	kV-Rr, 6kV, 0.3A, <500ns	=31a	(34x7x8mm)	-
1 S 2178	Org	Si-Di	kV-Rr, 6kV, 0.5A, <500ns	=31a	(37x8x11)	-
1 S 2179	Org	Si-Di	Rr, S, 1200V, 2A	=31a	(37x8x11) BY 228	=31a BY 228, BY 246/1200, BY 448, BY 458
1 S 2180(A)[Texas]	Tix	Z-Di	=1S2030[Texas]: 18V	31a	DO-7	-1S2030
1 S 2180 [Origin]	Org	Si-Di	kV-Rr, 12kV, 0.1A, <500ns	=31a	(32x6x7mm)	1N3052
1 S 2181 [Origin]	Org	Si-Di	kV-Rr, 36kV, 0.1A, <500ns	=31a	(111x140)	
1 S 2182 [Origin]	Org	Si-Di	kV-Rr, 30kV, 0.1A, <500ns			1N3061
1 S 2186	Tos	C-Di	VHF/UHF Band-S	31a	DO-35	BA 244, BA 282, BA 284, BA 482
1 S 2187	Tos	Si-Di	Schottky, UHF Mx, 2V, 30/90mA, F<10dB(900MHz)	31a	DO-7	BA 480...481, BAT 19, BAT 29
1 S 2188	Hit	C-Di	AFC, Tuning	31a	DO-35	-
1 S 2190	Nec	Ref-Di	7.7...8.7V(10mA), ±0.01%/°C, <20Ω, 0.25W	2c	TO-18	BZX 51, 1N4780
1 S 2191		Ref-Di	=1S2190: ±0.005%/°C	2c	TO-18	BZX 52, 1N4781
1 S 2192		Ref-Di	=1S2190: ±0.002%/°C	2c	TO-18	BZX 53, 1N4782
1 S 2193		Ref-Di	=1S2190: ±0.001%/°C	2c	TO-18	BZX 54, 1N4783
1 S 2194	Nec	Z-Di	5.4...6.6V, 0.25W	31a	DO-7	BZX55/..., BZX79/..., ZPD..., 1N5232...43,++
1 S 2195		Z-Di	=1S2194: 7.5...10V	31a	DO-7	
1 S 2196		Z-Di	=1S2194: 10.8...13.2V	31a	DO-7	
1 S 2197(A)	Hit	C-Di	AFC, Tuning	31a	DO-7	-
1 S 2198	Nec	Si-Di	Schottky, UHF Mx, 5V, 30mA, F<10.5<dB(855MHz)	31a	DO-7	BA 480...481, BAR 19, BAT 29
1 S 2199 [NEC]	Nec	Ge-Di	Tunnel-Di	34	DO-17	-
1 S 2200 [NEC]	Nec	Ge-Di	Tunnel-Di	34	DO-17	-
1 S 2200(A)[Texas]	Tix	Z-Di	=1S2030[Texas]: 20V	31a	DO-7	+1S2030
1 S 2204	Nec	Si-Di	SS, 70V, 0.2A, <7ns	31a	DO-35	BAW 62, BAX 95, 1N4446...49, 1N4148...49++
1 S 2206	Nec	C-Di	UHF AFC	71a(4mm)	SOD-23	BA 121, BB 117, BB 417, 1S789
1 S 2207	Nec	C-Di	VHF AFC	71a(4mm)	SOD-23	BA 125, BB 119, 1S114, 1S125
1 S 2208	Nec	C-Di	UHF Tuning	71a(4mm)	SOD-23	BB 105, BB 205, BB 305, BB 405, BB 505++
1 S 2209	Nec	C-Di	VHF Tuning	71a(4mm)	SOD-23	BB 105, BB 205, BB 305, BB 405, BB 505++
1 S 2210	Nec	Si-Di	Schottky, SS, 10/11V, 20/60mA, Uf<1V(20mA)	31a	DO-35	BAT 19, 1S588, 1S5106
1 S 2211	Nec	Si-Di	Schottky, SS, 30/33V, 35/100mA, Uf<1V(35mA)	31a	DO-35	BAT 81
1 S 2212	Nec	Si-Di	S, 30V, 0.1A, <100ns	31a	DO-35	BAV 17...20, BAX 90, BAX 94, 1N3070, ++
1 S 2220(A)[Texas]	Tix	Z-Di	=1S2030[Texas]: 22V	31a	DO-7	-1S2030
1 S 2222	Nec	C-Di	VHF/UHF Band-S	71a(4mm)	SOD-23	BA 244, BA 282, BA 284, BA 482
1 S 2223	Inr	Si-Di	Dual, Rr, 100V, 1.8A, Uf<0.9V(0.9A)	12j	(12x10x6)	2x (BY251...255, BY259/300, 1N5060...62++)
1 S 2224		Si-Di	=1S2223: 200V	12j	(12x10x6)	2x (BY251...255, BY259/300, 1N5060...62++)
1 S 2225		Si-Di	=1S2223: 400V	12j	(12x10x6)	2x (BY252...255, BY259/600, 1N5060...62++)
1 S 2223R...2225R		Si-Di	=1S2223:	12h	(12x10x6)	2x (BY251...255, BY259/..., 1N5060...62++)
1 S 2226	Inr	Si-Di	Rr, 100V, 1A, Uf<0.9V(1A)	31a	SOD-22	BY 126...127, BY 133...135, 1N4002...07, ++
1 S 2227		Si-Di	=1S2226: 200V	31a	SOD-22	BY 126...127, BY 133...134, 1N4003...07, ++
1 S 2228		Si-Di	=1S2226: 400V	31a	SOD-22	BY 126...127, BY 133...134, 1N4004...07, ++
1 S 2229		Si-Di	=1S2226: 600V	31a	SOD-22	BY 126...127, BY 133...134, 1N4005...07, ++
1 S 2230		Si-Di	=1S2226: 800V	31a	SOD-22	BY 127, BY 133, BY 227, 1N4006...07, ++
1 S 2231		Si-Di	=1S2226: 1000V	31a	SOD-22	BY 127, BY 133, BY 227, 1N4007, ++
1 S 2233	Tos	Si-Di	Rr, 600V, 1.5A, Uf<1.2V(2A)	34b	DO-1	BY 226...227, BY 253...255, 1N5397...99, ++
1 S 2234		Si-Di	=1S2233: 800V	34b	DO-1	BY 227, BY 254...255, 1N5398...99, ++
1 S 2235		Si-Di	=1S2233: 1000V	34b	DO-1	BY 227, BY 255, BYX 86, 1N5399, ++
1 S 2236	Tos	C-Di	FM AFC	31a	DO-35	BA 111, BA 124, 1S2790, 1S5V0, ++
1 S 2237(B)	Tos	Si-Di	kV-Rr, 18kV, 2mA, <250ns			BY 476, BY 711
1 S 2238 [Hitachi]	Hit	Si-Di	Rr, contr.av., 400V, 1.3A, Uf<1.4V(4A)	31a	SOD-57	BYW 53...56, 1N5060...5062
1 S 2239 [Hitachi]		Si-Di	=1S2238: 600V	31a	SOD-57	BYW 54...56, 1N5061...5062
1 S 2240 [Hitachi]		Si-Di	=1S2238: 800V	31a	SOD-57	BYW 55...56, 1N5062
1 S 2240(A)[Texas]	Tix	Z-Di	=1S2030[Texas]: 24V	31a	DO-7	+1S2030
1 S 2241	Hit	Si-Di	Rr, contr.av., 400V, 1.1A, Uf<1.75V(3.3A)	31a	SOD-57	BYW 53...56, 1N5060...5062
1 S 2242		Si-Di	=1S2241: 600V	31a	SOD-57	BYW 54...56, 1N5061...5062
1 S 2243		Si-Di	=1S2241: 800V	31a	SOD-57	BYW 55...56, 1N5062
1 S 2244	Hit	Si-Di	FR, 200V, 0.4A, Uf<1.95V(2.5A), <800ns	31a	SOD-57	BA 157...159, BY 204/4, BY 206...207, ++
1 S 2245		Si-Di	=1S2244: 400V	31a	SOD-57	BA 157...159, BY 204/4, BY 207, ++
1 S 2246		Si-Di	=1S2244: 600V	31a	SOD-57	BA 158...159, BY 204/8, BY 207, ++
1 S 2247	Mit	Si-Di	P Rr, 500V, 600A(Tc=90°), Uf<1.85V(1900A)		(17x31mmØ)	-
1 S 2248		Si-Di	=1S2247: 600V			-
1 S 2249		Si-Di	=1S2247: 800V			-
1 S 2250		Si-Di	=1S2247: 1000V			-
1 S 2251		Si-Di	=1S2247: 1200V			-
1 S 2252		Si-Di	=1S2247: 1500V			-
1 S 2253		Si-Di	=1S2247: 2000V			-
1 S 2254		Si-Di	=1S2247: 2500V			-
1 S 2255		Si-Di	=1S2247: 3000V			-
1 S 2256	Mit	Si-Di	P Rr, 1200V, 250A(Tc=111°), Uf<1.75V(780A)		(13x40mmØ)	-
1 S 2257		Si-Di	=1S2256: 1500V			-
1 S 2258		Si-Di	=1S2256: 1600V			-